

EE 2720, Spring 2011

Homework # 1

Due Wednesday February 9, 2011

in class

Enjoy your homework.

Alex

EE 2720, Homework #1 ①

Note: Please STAPLE your homework

Problem 1: Find the value of the unsigned binary number 10011101.011_2

Problem 2: Convert into octal the following binary number 1010011101.11_2

Problem 3: Convert into binary the following octal number 4567.75_8

Problem 4: Convert into hexadecimal the following binary number 1010011101.11_2

Problem 5: Convert into binary the following hexadecimal number $58E.A6_{16}$

Problem 6: Convert 173.625_{10} into binary

Problem 7: Convert 0.7_{10} into binary. What do you observe?

➡ NEXT PAGE ➡

Problem 8: What is the Dynamic Range (DR) of a 10-bit integer binary unsigned system?

Problem 9: Compute $X+Y$ where X and Y are the following 6-bit binary unsigned numbers: $X = 101011_2 = 43_{10}$; $Y = 010010_2 = 18_{10}$. When you do the addition show all the carries. Do you have an overflow in this case? Justify your answer.

Problem 10: Repeat problem 9 with $X = 101111_2 = 47_{10}$; $Y = 010111_2 = 23_{10}$.

Problem 11: What is the Dynamic Range (DR) of a 6-bit integer binary signed-magnitude system?

Problem 12: Find the 10^2 's complement of the number 35865_{10} . Use both ways for finding the 10^2 's complement of a number provided in handout #2.

➡ NEXT PAGE

EE 2720, HW#1 cont.

③

Problem 13: What is the Dynamic Range (DR) of an 8-bit integer binary two's-complement system?

Problem 14: Using the lemma on page 13 of handout #2 find the value of the following two's-complement number:
 11011011_2 .

Problem 15: Find the two's-complement of the number $X = 11011010_2$.

Problem 16: Using the two's-complement system perform $X - Y$ where
 $X = 101010_2 = -22_{10}$ and $Y = 000101_2 = +5_{10}$.