LSU EE 4720

Homework 2

Due: 21 February 2025

Formatted 16:21, 6 March 2025

Collaboration Rules

Each student is expected to complete his or her own assignment. It is okay to work with other students and to ask questions in order to get ideas on how to solve the problems or how to overcome some obstacle (be it a question of MIPS or assembler syntax, interpreting error messages, how a part of the problem might be solved, etc.) It is also acceptable to seek out assembly language resources for help on MIPS, etc. It is okay to make use of AI LLM tools such as ChatGPT and Copilot to generate sample code. (Do not assume LLM output is correct. Treat LLM output the same way one might treat legal advice given by a lawyer character in a movie: it may sound impressive, but it can range from sage advice to utter nonsense.)

After availing oneself to these resources each student is expected to be able to complete the assignment alone. Test questions will be based on homework questions and the assumed time needed to complete the question will be for a student who had solved the homework assignment on which it was based.

Student Expectations

Some of the problems require thought, and students are expected to persevere until they find a solution. It is each student's duty to him or herself to resolve frustrations and roadblocks quickly, hopefully helped along by the satisfaction of making progress. There are plenty of old problems and solutions to look at. One way to resolve issues is to ask Dr. Koppelman or others for help.


Resources

For examples of pipeline execution diagrams of given code fragments running on given MIPS implementations see past midterm exams (and final exams, but mostly midterms). The solutions to almost all past midterms in this course are available. A good place to start would be 2023 Midterm Exam Problem 2, 3, 4, and 5.

Problem 1: Solve this problem after Problem 2. It appears before Problem 2 so that you don't somehow forget it. Complete the first two parts 2024 Final Exam Problem 1, which asks for pipeline execution diagrams of MIPS implementations. Solve the parts on page 2 and 3. Do not solve the floating-point question on page 4.

There is another problem are on the next page.

Problem 2: Note: The following problem was assigned in all but one of the last eight years, and its solution is available. DO NOT look at the solution unless you are lost and can't get help elsewhere. Even in that case just glimpse. Appearing below are **incorrect** executions on the illustrated implementation. For each one explain why it is wrong and show the correct execution.



(a) Explain error and show correct execution.

```
# Cycle 0 1 2 3 4 5 6 7

lw r2, O(r4) IF ID EX ME WB

add r1, r2, r7 IF ID EX ME WB
```

(b) Explain error and show correct execution.

```
# Cycle 0 1 2 3 4 5 6 7
add r1, r2, r3 IF ID EX ME WB
lw r1, 0(r4) IF ID -> EX ME WB
```

(c) Explain error and show correct execution.

```
# Cycle 0 1 2 3 4 5 6 7
add r1, r2, r3 IF ID EX ME WB
sw r1, 0(r4) IF ID -> EX ME WB
```

(d) Explain error and show correct execution.

```
# Cycle 0 1 2 3 4 5 6 7
add r1, r2, r3 IF ID EX ME WB
xor r4, r1, r5 IF ----> ID EX ME WB
```